



Contour

Portable Power Supply



A Brilliant
Backup Power Source

www.sunsynkmobile.com
sales@sunsynkmobile.com

Powered by SUN  SYNK

Introducing the Contour

by Sunsynk Mobile.

The 'Contour' is an all-in-one power pack that can be used as an Uninterruptible Power System (UPS) connecting the mains and essential power loads.

This makes the device ideal for home offices where laptops, fridges and lights must keep running during load shedding/power outages.

It can also be used as a reliable portable power source wherever and whenever you need it.

It's the perfect combination of pure sine wave inverter and lithium phosphate batteries.



USB/C
Ports



AC & Solar
Charging



Battery Level
Indicator



Load Level
Indicator



AC & DC
Output



Contour
All-in-One Unit

<https://www.youtube.com/watch?v=MBPQ7uC9OBw>



Testing
the Contour

<https://www.youtube.com/watch?v=5a3d91-wMqA>



Our
Distributors

<https://www.sunsynk.org/ourdistributors>

Portable Power Station

- LiFePO4 battery.
- UPS function.
- 5V, 9V, 12V and 240V outputs.
- Built-in inverter.
- 1kWh and 2kWh versions.
- Portable with built-in wheels.
- Charge from the mains or solar.
- Battery charge level and system load indicator.



1000

1kW hybrid inverter
& 1kWh battery

(White only available in South Africa)



2000

1kW hybrid inverter
& 2kWh battery



| Model | Contour 1000 | Contour 2000 |
|--------------------------------------|---|---|
| Battery Input Parameters | | |
| Capacity | 1000W PSW Inverter | 1000W PSW Inverter |
| | 250W MPPT Charger | 250W MPPT Charger |
| | 250W AC Charger | 250W AC Charger |
| Mains Input (Charge) | AC 240V/50Hz | AC 240V/50Hz |
| Max. Charging Current (Mains) | 10A | 10A |
| | 250W AC Charger | 250W AC Charger |
| Solar Panel Voltage Range | 32V-60V | 32V-60V |
| Max. Charging Current (Solar Panels) | 10A | 10A |
| Solar Charger | 250W MPPT Charger | 250W MPPT Charger |
| Outputs | 2 x USB 5V 2A | 2 x USB 5V 2A |
| | 1 x Type C -18W | 1 x Type C -18W |
| | 1 x DC 9V 1A | 1 x DC 9V 1A |
| | 2 x DC 12V 1A | 2 x DC 12V 1A |
| AC Outlet | AC 240V/50Hz | AC 240V/50Hz |
| Case Material | Steel | Steel |
| Inverter Peak Wattage | 2000W (4s) | 2000W (4s) |
| Inverter Normal Max. Running Power | 1000W | 1000W |
| Max. Inverter Efficiency | >92% | >92% |
| Current Harmonic Distortion | >3% | >3% |
| Battery Data | | |
| Battery Type | LiFePO4 Lithium Iron Phosphate Battery Pack | LiFePO4 Lithium Iron Phosphate Battery Pack |
| Battery Specification | 1 x 25.6V - 36Ah - 921.6Wh Battery Packs | 2 x 25.6V - 36Ah - 921.6Wh Battery Packs |
| Total Battery Capacity | 921.6Wh | 1843.2Wh |
| Product Information | | |
| Weight | 25kg | 33kg |
| Dimensions (L x H x D mm) | 426.5 x 324.2 x 321.6 | 426.5 x 324.2 x 321.6 |



60 rounds of
toast

99 mugs of tea
(big ones)

26 smart phone
charges

06 hours of
television

Values based on Contour 2000



Contact Us

Email sales@sunsynkmobile.com

Website www.sunsynkmobile.com

Address 17 Turnstone Business Park, Mulberry Avenue, Widnes, Cheshire, WA8 0WN

Phone +44 151 832 4300