


CONTOUR 1000 & 2000


Portable Power.

Introducing the Contour 1000 & Contour 2000 by Sunsynk Mobile.

The Contour provides a portable uninterrupted power supply, even in the most remote settings. It's the perfect combination of pure sine wave inverter and lithium phosphate batteries.



USB/C
Ports




AC & Solar
Charging



Battery Level
Indicator



Load Level
Indicator



AC & DC
Output

Battery Input Parameters

Contour 1000 & 2000

Capacity	1000W PSW Inverter
	250W MPPT Charger
	250W AC Charger
Mains Input (Charge)	AC 240V/50Hz
Max. Charging Current (Mains)	10A
	250W AC Charger
Solar Panel Voltage Range	32V-60V
Max. Charging Current (Solar Panels)	10A
Solar Charger	250W MPPT Charger
Outputs	2 x USB 5V 2A
	1 x Type C - 18W
	1 x DC 9V 1A
	2 x DC 12V 1A
AC Outlet	AC240V/50Hz
Case Material	Steel
Inverter Peak Wattage	2000W (4S)
Inverter Normal Max. Running Power	1000W
Max. Inverter Efficiency	>92%
Current Harmonic Distortion	<3%

Battery Data	Contour 1000
Battery Type	LiFePO ₄ Lithium Iron Phosphate Battery Pack
Battery Specification	1 x 25.6V - 36Ah - 921.6Wh Battery Packs
Total Battery Capacity	921.6Wh
Battery Data	Contour 2000
Battery Type	LiFePO ₄ Lithium Iron Phosphate Battery Pack
Battery Specification	2 x 25.6V - 36Ah - 921.6Wh Battery Packs
Total Battery Capacity	1843.2Wh
Product Weight	
Contour 1000	25kg
Contour 2000	33kg